



## VHF AND UHF TRANSCEIVERS

**IC-F15**  
(VHF transceiver, rotary type)

**IC-F15S**  
(VHF transceiver, toggle type)

**IC-F25**  
(UHF transceiver, rotary type)

**IC-F25S**  
(UHF transceiver, toggle type)

### ***Built to last, built to work!***

- **Tough and reliable construction**
- **Simple operation**
- **Wide range frequency coverage**
- **Lithium-ion battery standard**
- **Built-in CTCSS and DTCS**
- **Multiple 2-Tone, Multiple 5-Tone**
- **Wide range of accessories available**



# Built to last, built to work!

---



*The IC-F15/S series shows Icom's sign. Simple operation for every tool for your daily business. Its resistant to shock and vibration. The locks the battery pack to the radio, Li-Ion battery pack, loud and clear and option unit connector combinations.*



## **Tough and reliable construction**

The IC-F1 5/S series is built around an aluminum die-cast chassis and covered with tough polycarbonate casing. This radio is built to last. Its dual slide rail securely locks the battery to the radio. The battery terminal is covered with a non-corrosive rubber packing. The belt clip is clamped between the radio and the battery, making it nearly impossible to knock loose.

## **Simple operation**

Having only 3 buttons, volume and channel knobs, the IC-F15/S series does not require special training to use. Positive button action for sure operation even when wearing gloves, allows you to get down to the business of communicating without fuss.

## **Wide frequency coverage**

The IC-F15/S series covers a wide frequency range with one version (136–174, 400–470MHz). Wide, middle and narrow channel spacing\* is programmable per channel.

(\* Programmable 25/12.5kHz or 20/12.5kHz)

VHF TRANSCEIVERS

**IC-F15**  
**IC-F15S**

UHF TRANSCEIVERS

**IC-F25**  
**IC-F25S**



's new direction in PMR radio de-  
 vone but a powerful and reliable  
 very durable construction is re-  
 he dual rail guide design securely  
 dio. Wide range frequency cover-  
 d clear audio, built-in signalings  
 bined with Icom grade electrical  
 s will easily exceed your expecta-

## OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.

### BATTERY PACKS



| Battery packs | Type and capacity<br>Li-Ion | Operating time* | Output power<br>(VHF/UHF) |
|---------------|-----------------------------|-----------------|---------------------------|
| BP-23         | 7.4V/ 800mAh                | 5.5 hours       | 5W/4W                     |
| BP-231        | Li-Ion<br>7.4V/1150mAh      | 8 hours         | 5W/4W                     |
| BP-232        | Li-Ion<br>7.4V/2000mAh      | 14 hours        | 5W/4W                     |

\* Operating time is approximate time (at 20 C).  
 Tx: Rx: standby=5:5:90.

### RAPID CHARGER



**BC-160 DESKTOP CHARGER + BC-145AC ADAPTER**  
 Charges the BP-231 in 2 hours (approx.).

**BC-119N DESKTOP CHARGER + AD-1 06 CHARGER ADAPTER**  
 + **BC-145AC ADAPTER** : Charges the BP-231 in 2 hours (approx.).  
**CP-17L CIGARETTE LIGHTER CABLE, OPC-515L DC POWER CABLE**  
 For use with the BC-160 or BC-119N. (12-16V DC required).

### BELT CLIPS



**MB-93** : Swivel type. A fast and easy way to remove the transceiver from your belt.

**MB-94** : Alligator type. Same as supplied.

### MULTI-CHARGER



**BC-121N MULTI-CHARGER + AD-106 CHARGER ADAPTER**  
 + **BC-124AC ADAPTER** (Six AD-106s are required)  
 Charges up to 6 battery packs in 2 hours (approx.) when BP-231 is attached.

**OPC-656 DC POWER CABLE** : For use with the BC-121N. (12-20V DC required).

### LEATHER BELT HANGERS



**MB-96N**: Swivel type belt hanger. Swivel joint of the MB-93 included.

**MB-96F**: Fixed type belt hanger. For use with MB-94.

### HEADSETS and PTT/VOX UNIT



**HS-94**: Earhook headset with flexible boom microphone.  
**HS-95**: Behind-the-head headset with flexible boom microphone.  
**HS-97**: Throat microphone fits around your neck and picks up speech vibration.  
**VS-1L**: PTT/VOX unit. Required when using these headsets with the transceiver.

### SPEAKER-MICROPHONE



**HM-131L**: Durable body. Equipped with an earphone jack and revolving clip.

### INTERNAL UNITS



**UT-108** : Provides DTMF. Selective call and ANI capabilities.  
**UT-1 09** : Up to 32 scrambling codes are available. Version 01 is required.  
**UT-110**: Up to 1020 scrambling codes are available. Version 01 is required.  
**UT-113** : Automatically sends an emergency signal when the transceiver is left in a horizontal position for a preset time.

**SP-13** : EARPHONE  
 Provides clear audio in noisy environments.  
**STUBBY ANTENNAS**  
 • **FA-SC56VS** : 146-162MHz  
 • **FA-SC57VS** : 160-174MHz  
 • **FA-SC73US** : 450-490MHz  
**ANTENNAS**  
 • **FA-SC25V** : 136-150MHz  
 • **FA-SC55V** : 146-174MHz  
 • **FA-SC25U** : 400-430MHz  
 • **FA-SC57U** : 430-470MHz

## Lithium-Ion battery standard

The IC-F15/S series comes with the BP-231 Li-Ion battery pack as standard. Li-Ion batteries have virtually no memory issues and allows you flexible charging. In addition, the optional BP-232 provides a high capacity 2000mAh for longer operating time.

## Optional board

The IC-F15/S series has an expansion socket for adding an optional board. Voice scrambler, man down and DTMF decoder features are available, depending on the installed board.

## Most popular signalings built-in

Use the built-in 2-Tone, 5-Tone, CTCSS and DTCS capabilities as standard to set up your own talk groups and quiet standby when others are talking.

## Multiple 2-Tone, Multiple 5-Tone

Up to 10 2-Tone/8 5-Tone codes can be decoded on a channel. When a matched tone is received, the following items are programmable for each code.

- Beep sound • Answer back • Stun
- LED blink • Auto transmit • Scan

## Other features

- LED low battery alert
- TOT function and lock out penalty timer
- 2 step power saver
- Normal and priority scan
- 500mW loud and clear audio
- Optional VOX headset for hands free operation
- PC programming capability
- Embedded ESN (Electronic serial



**SPECIFICATIONS**

| GENERAL                                |  |
|--|--|
| • Frequency range                      | :<br>IC-F15/IC-F15S 136–174MHz<br>IC-F25/IC-F25S 400–470MHz      |
| • Number of channels                   | : 16 (IC-F15, IC-F25)<br>4 (Max., IC-F15S, IC-F25S)              |
| • Channel spacing                      | : 12.5kHz/20kHz/25kHz  |
| • PLL channel step                     | : 2.5kHz, 3.125kHz (VHF)<br>5kHz, 6.25kHz (UHF)                  |
| • Power supply requirement:            | 7.2V DC  |
| • Current drain (at 7.2V DC; approx.): |  |
| Transmit VHF (5W)                      | 1.5A   |
| UHF (4W)                               | 1.6A   |
| Receive stand-by                       | 70mA   |
| rated output                           | 300mA  |
| • <del>Antenna</del>                   | : 50 Ω   |
| • Usable temperature range             | : –25°C to +55°C   |
| • Dimensions (with BP-231)             | : 53 (W) × 120 (H) × 38 (D) mm<br>(projections are not included) |
| • Weight (approx. with BP-231)         | : 260g   |

| TRANSMITTER                               |   |
|---|---|
| • Output power                            | : 5W (VHF), 4W (UHF)  |
| • Max. frequency deviation                | : ±5kHz (Wide)<br>±4kHz (Middle)<br>±2.5kHz (Narrow)  |
| • Frequency error                         | : ±2.5ppm   |
| • Spurious emissions                      | : 0.25µW (below 1GHz)<br>1.0µW (above 1GHz)   |
| • <del>Antenna</del>                      | :<br>VHF 80dB typ. (Wide, middle)<br>70dB typ. (Narrow)<br>UHF 75/73/68dB typ. (Wide/middle/narrow) |
| • Residual modulation (With CCITT filter) | : 55dB typ. (Wide)<br>53dB typ. (Middle)<br>50dB typ. (Narrow)                                      |
| • Audio harmonic distortion               | : 3% typ. (AF 1kHz, 40% deviation)  |
| • Modulation limiting                     | : 60–100% of max. deviation   |
| • External microphone connector           | : 3-conductor 2.5 (d) mm /2.2kΩ   |

| RECEIVER                                  |  |
|---|--|
| • Sensitivity                             | : –4dBµV typ. (emf, at 20dB SINAD)                             |
| • Squelch sensitivity                     | : –4dBµV typ. (emf, at threshold)                              |
| • Adjacent channel selectivity:           |  |
| VHF                                       | 75dB typ. (Wide, middle)<br>65dB typ. (Narrow)                 |
| UHF                                       | 75/73/65dB typ. (Wide, middle, narrow)                         |
| • Spurious response                       | : 70dB   |
| • Intermodulation                         | : 67dB typ.  |
| • Hum and noise ratio (with CCITT FILTER) | : 55dB typ. (Wide)<br>53dB typ. (Middle)<br>50dB typ. (Narrow) |
| • Audio output power                      | : 500 mW t y p .<br>(at 5% distortion with an 8Ω load)         |
| • External speaker connector:             | 2-conductor 3.5 (d) mm/8Ω                                      |

Measurements made in accordance with EN 300-086.  
All stated specifications are subject to change without notice or obligation.



**Your Distributor/Dealer:**



**Communication Specialists Ltd. Unit 20, Murrell Green Business Park,  
London Road, Hook, Hampshire. RG27 9GR United Kingdom**  
**Tel. +44(0)1256766600 Fax. +44(0)1256766500**  
**www.comm-spec.com info@comm-spec.co.uk**

